







VOCO V-ZONE BENEFITS

EASY WIRELESS SET UP

Set-up using your home Wi-Fi or simply plug the V-Spot into ethernet for simple configuration.

WHY STOP AT ONE

Add VOCO devices to create a multi-zone media system to enjoy music and video throughout your home.

BUILT IN MUSIC SERVER

The VOCO V-Zone comes with a built in music server that automatically finds music when an iPod, mp3 or USB hard drive is plugged in.

FASTER VOICE SEARCHING

Download the VOCO Controller app from The Apple App Store® or Google Play® and use your voice to search and manage music, internet radio and online music services.

STREAM UNLIMITED MUSIC

Experience the ultimate music experience by streaming unlimited music.

iTunes® PANDORA®













The First of Its Kind.

Only VOCO delivers the ultimate music experience by combining HiFi sound, HD video and voice search so you can listen and watch your favorite performers. Don't settle for half the experience when you can stream music and video in any room wirelessly. VOCO gets it™. VOCO created easier and more efficient ways to search, manage, and play music and video in any room; along with the freedom to access and control it using mobile devices. VOCO offers multi-room streaming, voice search, Wi-Fi hotspot, streaming from computers, iTunes®, YouTube®, phones, tablets, USB drives, and free online services like Pandora®, Spotify®, Tunein® and many others.

Music

Audio Output: 2 CH DAC, 102dB dynamic range

Music Services: Pandora, Murfie, Sky FM, Tunein, Jazz Radio

Digitally Imported

Audio Formats:

Natively Supported Formats:

| Type Of File: | Max Bitrate | Frequency | Metadata |
|---------------|-------------|--------------|----------|
| MP3 | 320 Kbps | up to 48 KHz | Yes |
| FLAC | 320 Kbps | up to 48 KHz | Yes |
| AAC/M4A | | up to 48 KHz | |
| Ogg | 320 Kbps | up to 48 KHz | Yes |

Formats requiring external VMS:

| Type Of File: | Max Bitrate | Frequency | Metadata | VMS Supported |
|----------------|-------------|--------------|----------|---------------|
| WMA | 320 Kbps | up to 48 KHz | Yes | Windows PC |
| WMA Lossless | 320 Kbps | up to 48 KHz | Yes | Windows PC |
| WMA Pro | 320 Kbps | up to 48 KHz | Yes | Windows PC |
| WAV | 320 Kbps | up to 48 KHz | Yes | PC, NAS, OSX |
| Apple Lossless | 320 Kbps | up to 48 KHz | Yes | PC, NAS, OSX |

Playlists Supported: .m3u, .pls, .asx, .cue, .wpl

Playback Modes: Shuffle, repeat

Operating Systems (For Stored Files): MAC or PC (optional for using computer as a music source): Windows XP, Vista. 7 or 8®.

100mb available hard drive space

Nas Formats: ReadyNAS Ultra 2/2+4/4+6/6+, ReadyNAS Pro 2/4/6

Networking

Wireless Connectivity: 802.11 b/g/n

Ethernet port: 10/100 Ethernet

Antenna Type: External

Access Point: Configurable as an access point (Hotspot) using

Ethernet or wirelessly to expand your Wi-Fi footprint.

General

Power Supply: AC100-240V 50/60Hz 0.6A, DC 12V 2A

Dimensions: 7.1" 180mm (W) x 1.4" 35.5mm (H) x 4.2" 106mm (D)

Weight: 2.88 Pounds

Package Contents: VOCO V-Zone, Power Adapter, 3.5mm RCA

Stereo Audio Cable, Ethernet Cable

VOCO Controller App Available at:





USB Drive: 1 USB 2.0 (charges devices, 5V 1A)

Language Support: English, Spanish, French, German and Dutch

Product Finish: Black gloss finish on top, matte black on sides.

LED Light Meaning: Solid Red: VOCO Device is starting up Blinking Red: VOCO Device is installing base firmware Blinking Green: VOCO Device is looking for a Wi-Fi network

Solid Amber: Connected to Ethernet

Solid Green and Blinking Blue: VOCO Device is on a network, but music sever is unavailable. Playback is not possible, please select a new My Music Server. Solid Green and Blinking Blue and Red: VOCO Device is downloading firmware packages. Amber light will be on if connected to Ethernet

Additional Features

Expanded Jackpack:

V-ZONE BACK

